

HPL Commands on HP362 computer

Note: the currently loaded computer software must be halted before executing any of the commands listed below.

To halt the program....

Press simultaneously: shift + reset

To format the internal hard disk:

Type: init":s1406,0",302

Press: Select

To format a 3.5" Floppy Diskette (careful! Do not accidentally format the hard disk!)

Type: init":s1400,0",302

Press: Select

To format a 3.5" Floppy Diskette to transfer a file to a PC computer (PC Format, not HPL!!)

Type: init":p1400,0"

Press: Select

To display the contents of the current directory

Type: cat

Press: Select

To change directories

Press simultaneously: shift + reset

Type: msi"directory_name"

Press: Select

To erase a file on hard disk:

Type: kill"filename"

Press: Select

To copy a file from hard disk to floppy (if the file already exists, you must erase it first)

Type: copy"Directory_Name/FileName:s1406,0", " Directory_Name/FileName:s1400,0"

Press: Select

To copy a file from floppy to hard disk (if the file already exists, you must erase it first)

Type: copy"Directory_Name/FileName:s1400,0", " Directory_Name/FileName:s1406,0"

Press: Select

To back up the SYSTEM_HPL file on the hard disk that is unique to the ID MODULE on your HP362:

Insert your variable backup diskette for the target stepper into the HP362 floppy disk drive

Type: copy"SYSTEMS/SYSTEM_HPL:s1406,0", " SYSTEMS/SYSTEM_HPL:s1400,0"

Press: Select

To copy the SYSTEM_HPL file on a floppy disk to the freshly formatted hard disk:

Insert your variable backup diskette for the target stepper into the HP362 floppy disk drive

Type: copy"SYSTEMS/SYSTEM_HPL:s1400,0", " SYSTEMS/SYSTEM_HPL:s1406,0"

Press: Select